

STXB10RHULLMDS

| MOTOR HP | RPM | | STATIC PRESSURE IN INCHES W.G. | | | | | | | | |
|----------|------|-------|--------------------------------|-------|------|-------|------|-------|------|-------|------|
| | | | 0 | 0.125 | 0.25 | 0.375 | 0.5 | 0.625 | 0.75 | 0.875 | 1 |
| 1/4 | 650 | CFM | 545 | 348 | - | - | - | - | - | - | - |
| | | BHP | 0.01 | 0.01 | - | - | - | - | - | - | - |
| | | SONES | 2.6 | 2.0 | - | - | - | - | - | - | - |
| 1/4 | 750 | CFM | 629 | 468 | - | - | - | - | - | - | - |
| | | BHP | 0.02 | 0.03 | - | - | - | - | - | - | - |
| | | SONES | 3.6 | 2.9 | - | - | - | - | - | - | - |
| 1/4 | 850 | CFM | 713 | 575 | 384 | - | - | - | - | - | - |
| | | BHP | 0.03 | 0.04 | 0.04 | - | - | - | - | - | - |
| | | SONES | 4.6 | 3.9 | 3.6 | - | - | - | - | - | - |
| 1/4 | 950 | CFM | 797 | 675 | 533 | - | - | - | - | - | - |
| | | BHP | 0.04 | 0.05 | 0.05 | - | - | - | - | - | - |
| | | SONES | 5.5 | 4.9 | 4.5 | - | - | - | - | - | - |
| 1/4 | 1050 | CFM | 881 | 771 | 651 | 488 | - | - | - | - | - |
| | | BHP | 0.06 | 0.06 | 0.07 | 0.07 | - | - | - | - | - |
| | | SONES | 6.5 | 6.0 | 5.6 | 5.4 | - | - | - | - | - |
| 1/4 | 1150 | CFM | 965 | 864 | 758 | 636 | - | - | - | - | - |
| | | BHP | 0.07 | 0.08 | 0.09 | 0.10 | - | - | - | - | - |
| | | SONES | 7.6 | 7.2 | 6.7 | 6.5 | - | - | - | - | - |
| 1/4 | 1250 | CFM | 1049 | 958 | 862 | 757 | 628 | - | - | - | - |
| | | BHP | 0.09 | 0.10 | 0.11 | 0.12 | 0.12 | - | - | - | - |
| | | SONES | 8.9 | 8.5 | 8.0 | 7.7 | 7.5 | - | - | - | - |
| 1/4 | 1350 | CFM | 1132 | 1050 | 961 | 866 | 762 | 619 | - | - | - |
| | | BHP | 0.12 | 0.13 | 0.14 | 0.15 | 0.15 | 0.16 | - | - | - |
| | | SONES | 10.2 | 9.9 | 9.4 | 8.9 | 8.8 | 8.7 | - | - | - |
| 1/4 | 1450 | CFM | 1216 | 1141 | 1057 | 973 | 881 | 774 | 610 | - | - |
| | | BHP | 0.14 | 0.16 | 0.17 | 0.18 | 0.19 | 0.19 | 0.19 | - | - |
| | | SONES | 11.7 | 11.4 | 10.9 | 10.4 | 10.2 | 10.0 | 9.9 | - | - |
| 1/4 | 1550 | CFM | 1300 | 1230 | 1151 | 1076 | 991 | 902 | 797 | 615 | - |
| | | BHP | 0.18 | 0.19 | 0.20 | 0.21 | 0.22 | 0.23 | 0.24 | 0.23 | - |
| | | SONES | 13.1 | 12.7 | 12.3 | 11.9 | 11.5 | 11.3 | 11.2 | 11.0 | - |
| 1/3 | 1650 | CFM | 1384 | 1319 | 1245 | 1174 | 1098 | 1018 | 930 | 825 | 638 |
| | | BHP | 0.21 | 0.23 | 0.24 | 0.25 | 0.26 | 0.27 | 0.28 | 0.29 | 0.28 |
| | | SONES | 14.3 | 13.9 | 13.5 | 13.1 | 12.6 | 12.4 | 12.3 | 12.1 | 12.0 |
| 1/3 | 1750 | CFM | 1468 | 1407 | 1338 | 1270 | 1201 | 1126 | 1050 | 962 | 860 |
| | | BHP | 0.25 | 0.27 | 0.28 | 0.29 | 0.30 | 0.32 | 0.33 | 0.34 | 0.34 |
| | | SONES | 15.5 | 15.1 | 14.8 | 14.4 | 13.9 | 13.5 | 13.4 | 13.3 | 13.2 |